



## SSCN3904GN1

### NPN Switching Transistor

#### ➤ Features

VCB	VCE	VBE	IC
60V	40V	6V	200mA

#### ➤ Description

The NPN Transistor is designed for use in linear and switching applications. The device is housed in the DFN1006-3L package, which is designed for telephony and professional communication equipment.


#### ➤ Applications

- General purpose switching and amplification
- Telephony and professional communication equipment


#### ➤ Ordering Information

Device	Package	Shipping
SSCN3904GN1	DFN1006-3L	10000/Reel


#### ➤ Pin configuration



**DFN1006-3L (Bottom View)**



**Circuit Diagram**



**Marking (Top View)**



➤ **Absolute Maximum Ratings**( $T_A=25^{\circ}\text{C}$  unless otherwise noted)


Parameter	Symbol	Value	Unit
Collector-Base Voltage	$V_{CB0}$	60	V
Collector- Emitter Voltage	$V_{CEO}$	40	V
Emitter-Base Voltage	$V_{EBO}$	6	V
Collector Current-Continuous	$I_C$	200	mA
Collector Power Dissipation	$P_C$	100	mW
Thermal Resistance from Junction to Ambient	$R_{\theta JA}$	1250	$^{\circ}\text{C}/\text{W}$
Junction Temperature	$T_J$	150	$^{\circ}\text{C}$
Storage Temperature	$T_{STG}$	-55 to 150	$^{\circ}\text{C}$

➤ **Electrical Characteristics** ( $T_A=25^{\circ}\text{C}$  unless otherwise noted)


Parameter	Symbol	Test Conditions	Min.	Typ.	Max.	Unit
Collector-Base Breakdown Voltage	$BV_{CB0}$	$I_C=10\mu\text{A}, I_E=0$	60			V
Collector-emitter Breakdown Voltage	$BV_{CEO}$	$I_C=1\text{mA}, I_B=0$	40			V
Emitter -Base Breakdown Voltage	$BV_{EBO}$	$I_E=10\mu\text{A}, I_C=0$	6			V
Collector Cutoff Current	$I_{CEX}$	$V_{CE}=30\text{V}, V_{EB}=3\text{V}$			50	nA
Collector Cutoff Current	$I_{CBO}$	$V_{CB}=30\text{V}, I_E=0$			100	nA
Emitter Cutoff Current	$I_{EBO}$	$V_{EB}=3\text{V}, I_C=0$			100	nA
DC Current Gain	$h_{FE}$	$V_{CE}=1\text{V}, I_C=10\text{mA}$	100		300	
		$V_{CE}=1\text{V}, I_C=0.1\text{mA}$	40			
		$V_{CE}=1\text{V}, I_C=100\text{mA}$	30			
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C=50\text{mA}, I_B=5\text{mA}$			0.3	V
Base-Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C=50\text{mA}, I_B=5\text{mA}$			0.95	V
Transition frequency	$f_T$	$V_{CE}=20\text{V}, I_C=10\text{mA}$ $f=100\text{MHz}$	250			MHz
Delay Time	$t_d$	$V_{CC}=3\text{V}, V_{BE(off)}=-0.5\text{V}$ $I_C=10\text{mA}, I_{B1}=1\text{mA}$			35	ns
Rise Time	$t_r$	$V_{CC}=3\text{V}, V_{BE(off)}=-0.5\text{V}$ $I_C=10\text{mA}, I_{B1}=1\text{mA}$			35	ns
Storage Time	$t_s$	$V_{CC}=3\text{V}, I_C=10\text{mA}$ $I_{B1}=I_{B2}=1\text{mA}$			200	ns
Fall Time	$t_f$	$V_{CC}=3\text{V}, I_C=10\text{mA}$ $I_{B1}=I_{B2}=1\text{mA}$			50	ns




➤ **Typical Performance Characteristics ( $T_A=25^\circ\text{C}$  unless otherwise noted)**




**Collector Current vs. Base-Emitter Voltage**




**DC Current Gain vs. Collector Current**




**$V_{BE(sat)}$  vs. Collector Current**



**$V_{CE(sat)}$  vs. Collector Current**



**Power derating vs. Ambient temperature**



**Transition Frequency vs. Collector Current**




## ➤ Package Information

### Mechanical Data


Case: DFN1006-3L

Case Material: Molded Plastic. UL Flammability



DIM	Millimeters		
	Min	Nom	Max
A	0.45	0.50	0.55
A1	0.00	0.02	0.05
b	0.45	0.50	0.55
b1	0.10	0.15	0.20
c	0.12	0.15	0.18
D	0.95	1.00	1.05
e	0.65 BSC		
E	0.55	0.60	0.65
E1	0.15	0.20	0.25
L	0.20	0.25	0.30
L1	0.05REF		

### Suggested Pad Layout



DIM	Millimeters
C	0.25
X	0.65
Y1	0.50
Y2	0.50
Y3	0.25
Z	0.20



## DISCLAIMER

AFSEMI RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. AFSEMI DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICIENCE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

THE GRAPHS PROVIDED IN THIS DOCUMENT ARE STATISTICAL SUMMARIES BASED ON A LIMITED NUMBER OF SAMPLES AND ARE PROVIDED FOR INFORMATIONAL PURPOSE ONLY. THE PERFORMANCE CHARACTERISTICS LISTED IN THEM ARE NOT TESTED OR GUARANTEED. IN SOME GRAPHS, THE DATA PRESENTED MAY BE OUTSIDE THE SPECIFIED OPERATING RANGE (E.G. OUTSIDE SPECIFIED POWER SUPPLY RANGE) AND THEREFORE OUTSIDE THE WARRANTED RANGE.